How-to

This book is my personal knowledge collection.

- Configure UPS (Eaton 5E) in Debian bullseye
- Config for `simple-radio`
- MKV merge audio
- Resize Partition

Configure UPS (Eaton 5E) in Debian bullseye

This is the configuration for my `bananapi` with Debian `bullseye` and an `Eaton 5E` UPS connected via USB cable.

Configure USB

First, connect the UPS to the USB port and check if it is recognized by the system.

```
lsusb
```

The output should be something like this:

```
Bus 002 Device 001: ID 1d6b:0001 Linux Foundation 1.1 root hub
Bus 001 Device 003: ID 0463:ffff MGE UPS Systems UPS
Bus 001 Device 002: ID 1a40:0101 Terminus Technology Inc. Hub
Bus 001 Device 001: ID 1d6b:0002 Linux Foundation 2.0 root hub
```

Note the `0463:ffff` part, this is the `vendor:product` ID of the UPS.

Install packages

```
apt install nut
```

Configure NUT

Edit the file `/etc/nut/nut.conf` and add the following lines:

```
MODE=standalone
```

Edit the file `/etc/nut/ups.conf` and add the following lines:

```
xretry = 5
pollinterval = 5

[eaton5e]
    driver = usbhid-ups
    port = auto
    desc = "Eaton 5E"
    vendorid = 0463
    pollfreq = 30
```

Edit the file `/etc/nut/upsd.conf` and add the following lines:

```
LISTEN 127.0.0.1 3493
LISTEN 192.168.1.2 3493
```

Note, that I have added the IP address of my `bananapi` to the `LISTEN` line. This is because I want to monitor the UPS from my `home assistant` instance running on a different machine.

Edit the file `/etc/nut/upsd.users` and add the following lines:

```
[username]
  password = SuperSecretPassword
  actions = SET
  instcmds = ALL
  upsmon master
```

You should edit the `username` and `password` to your liking.

Start NUT

```
sudo upsdrvctl start
sudo upsd -c reload  # in case you have changed the config ()
```

```
systemctl restart nut-server
systemctl enable nut-server   # run the service at boot
```

Check UPS status

One way to check the UPS status is to use the `upsc` command.

```
sudo upsc eaton5e
```

The output should be something like this:

```
Init SSL without certificate database
battery.charge: 53
battery.runtime: 428
battery.type: PbAc
device.mfr: EATON
device.model: 5E 850i
device.type: ups
driver.name: usbhid-ups
driver.parameter.pollfreq: 30
driver.parameter.pollinterval: 5
driver.parameter.port: auto
driver.parameter.synchronous: no
driver.parameter.vendorid: 0463
driver.version: 2.7.4
driver.version.data: MGE HID 1.40
driver.version.internal: 0.41
input.voltage: 240.0
outlet.1.status: on
outlet.desc: Main Outlet
outlet.id: 1
outlet.switchable: no
output.frequency: 49.9
output.frequency.nominal: 50
output.voltage: 236.0
output.voltage.nominal: 230
ups.beeper.status: enabled
ups.delay.shutdown: 20
ups.firmware: 03.08.0018
ups.load: 31
ups.mfr: EATON
ups.model: 5E 850i
ups.power.nominal: 850
ups.productid: ffff
ups.start.battery: yes
ups.status: OL
```

```
ups.timer.shutdown: -1
ups.vendorid: 0463
```

Configure Home Assistant

There is a `nut` integration for `home assistant` that can be used to monitor the UPS. You can simply find it and configure it via the `integrations` page in `home assistant`. You need to provide the IP address of the machine running `nut` and the `username` and `password` you have configured in the `upsd.users` file.

References

- https://mic22.medium.com/basic-nut-configuration-for-green-cell-ups-and-home-assistant-integration-e08affcc54f

Config for `simple-radio`

Simple-Radio

`config.yml`

```
- name: 'Radio 357'
  url: 'https://stream.rcs.revma.com/an1ugyygzk8uv'
- name: 'Nowy Swiat'
  url: 'https://stream.nowyswiat.online/mp3'
- name: "RadioRAM"
  url: "http://stream4.nadaje.com:9220/ram"
- name: "Eska"
  url: "https://pldm.ml/radio?url=https://www.eskago.pl/radio/eska-wroclaw"
```

MKV merge audio

Extract audio from MP4 movie file

```
ffmpeg -i input_dubbing_PL.mp4 -vn --codec copy pl_audio.aac
```

Note: `-vn` option means *no video*. Only audio is being extracted.

Add second audio track to existing MKV file

The following command will create the file `output.mkv` with two audio tracks:

- `pl` - the track to be added
- `en` - original audio track existing in `input.mkv` movie file.

```
mkvmerge -o output.mkv --language 0:pl pl_audio.aac --language 1:en input.mkv
```

Resize Partition

```

```

```
sudo parted /dev/sda
print
resizepart
```